

Robur introduced the Time Delay Drawer Pedestal in Northern Europe more than fourty years ago. Since then, almost one hundred thousands units have been installed. Many different models have been developed at customers' request through the years. The RSH NF serie is specially designed for storage of documents.





Modern design painted in silver metallic.

The unit is equipped with Robur's unique pincode lock, which is integrated into the construction. From the keyboard individual codes and time delays can easily be programmed for each drawer.

The unit has keylock switch which activates the pincode-lock.



One stationary tray in the top drawer of RSH 2000 NF-2 and RSH NF-2H. Two movable dividers in upper drawer of RSH 2000 NF-2 and RSH NF-2H. No internal fittings in RSH 2000 NF-4.



Each unit is connected to the mains 240 A.C. by a transformer. Operating Voltage 12 A.C. Maximum power use is 1,6A. A backup battery is available on request.



The height can be adjusted. RSH 2000 NF-4 is prepared for anchoring with two holes at the bottom.

PRODUCT SPECIFICATIONS

	RSH 2000 NF-2	RSH 2000 NF-2H	RSH 2000 NF-4
Model			
External measurements H * W * D* mm	610 * 428 * 605	720 up to 745 * 428 * 605	1285 up to 1310 * 498 * 1022
Internal measurements of the drawers H*W*D*mm	Upper: 108 * 330 * 530 Bottom: 278 * 330 * 530	Each: 278 * 330 * 530	Each: 278 * 330 * 530
Weight ^{kg}	67	76	131
Height adjustment	If the wheels are removed the height will be 536mm.	The height can be adjusted with adjustable feet between 720 and 745 mm. Height without the adjustable feet: 708mm	The height can be adjusted with adjustable feet between 1285 and 1310 mm. Height without the adjustable feet: 1273mm
Anchoring	Has wheels for easier moving.	Placed under the workplace and attached to the desk.	Prepared for anchoring to the floor.
Drawers	One pencil drawer and two safety drawers	One pencil drawer and two safety drawers	Four safety drawers
Standard fittings	Plastic tray For pens, binders etc.	Plastic tray For pens, binders etc.	No fittings
* Excluding handle (+45 mm).			



Two stickers are supplied with the security drawer, one should be placed on the unit and the other one should be placed at the entrance.

OPTIONAL FITTINGS

- Silent alarm
- Battery backup box
- Emergency lock

We reserve the right to alter the specification without prior notice.



Head office: Robur Safe AB Lundbyvägen 8 311 68, Slöinge Sweden

└ + 46 346 260 260
└ info@robursafe.com
⊕ www.robursafe.com