



Security drawers with time delay

RSH 2000

Robur introduced the Time Delay Drawer Pedestal in Northern Europe more than forty years ago. Since then, almost one hundred thousands units have been installed. Many different models have been developed at customers' request through the years. RSH 2000 is designed for storage of banknotes, coins and forms during working hours. The unit is also suitable for storage of coins over night



Modern design painted in silver metallic.



The unit is equipped with Robur's unique pincode lock, which is integrated into the construction. From the keyboard individual codes and time delays can easily be programmed for each drawer.

The unit has keylock switch which activates the pincode-lock.



A chute for depositing banknotes into the bottom drawer is situated on the top left hand side (right hand on special order).

The top drawer has a stationary tray.

The two upper security drawers are for funds which the cashier needs to have easily available. Depending on working procedures coins, foreign currencies and/or forms may also be stored.

The bottom drawer receives and protects banknotes deposited through the chute.



Each unit is connected to the mains 230-240V A.C. by a transformer.

Operating Voltage 12 A.C. Maximum power use is 1,6A.

A backup battery is available on request.



The height can be adjusted with adjustable feet.

The unit is prepared for anchoring with two holes at the bottom. (Bolts are not included).

PRODUCT SPECIFICATIONS

	RSH 2000
External measurements H * W * D* mm	690 up to 715 * 450 * 400
Height adjustment	The height can be adjusted with adjustable feet between 690 and 715 mm. Height without the adjustable feet: 678.5 mm
Internal measurements of the two upper drawers H * W * D mm	125 * 330 * 325
Internal measurements of the bottom drawer H * W * D mm	165 * 330 * 325
Weight kg	63
Deposit function	Yes

* Excluding handle (+45 mm).

STANDARD FITTINGS



Plastic tray
For pens, binders etc.



Two stickers are supplied with the security drawer, one should be placed on the unit and the other one should be placed at the entrance.




Two movable dividers
In each of the two upper security drawers

OPTIONAL FITTINGS



Box for notes
With 9 dividers



Note rack
With coin inserts



Collection box

Note rack with coin inserts - €
1-Cent, 2-Cent, 5-Cent, 10-Cent, 20-Cent, 50-Cent, 1-€ och 2-€

- Battery backup box
- Silent alarm
- Emergency lock

We reserve the right to alter the specification without prior notice.



Head office:
Robur Safe AB
Lundbyvägen 8
311 68, Slöinge
Sweden

+ 46 346 260 260
info@robursafe.com
www.robursafe.com